

LED RTS 24V DC Receiver

Item #: 1870872

OVERVIEW:

Flexible and powerful LED lighting receiver. Programmable as 4 independently controlled dimmable outputs or as an RGB full color + 1 single color with 100W per output. Cover all your large zone lighting needs with the same RTS transmitter used to control pergolas, awnings, screens, shades and shutters.



TECHNICAL SPECIFICATIONS:

- | | |
|-----------------------------|--|
| ▪ Voltage: | 24V DC |
| ▪ IP: | 65 |
| ▪ Current Max (per output): | 4.2A |
| ▪ Radio Technology Somfy®: | Embedded |
| ▪ Single Color Outputs: | 4 x 100W |
| ▪ RGB + 1 Color Output: | 100W x 3 + 100W x 1 |
| ▪ Operating Temp: | 14°F to 140°F (-10°C / +60°C) |
| ▪ Dimensions: | 7.28 x 3.9 x 2.24 Inches (185 x 99 x 57mm) |

FEATURES SUMMARY:

- Use the same transmitters to control motorized products and area lighting
- Powerful 100W of LED lighting per zone for 400W of LED lighting possible per control
 - 4 independent 100W outputs will cover 4 zones of single-color light
 - RGB+1 mode provides full-color control for accent lighting plus an independent single color lighting zone, both with full dimming control
- Built-in and optional remote antenna to ensure reliable radio reception
- Simple user control of light level and color using the standard Somfy RTS transmitter or the incremental control of the Situio® Variation
- Favorite "MY" position
- Fun mood lighting options in RGB mode:
 - Lights auto dim up and down, speed and color controllable
 - Lights flash on/off, color and speed of flash controllable
 - Lights vary color automatically, speed of color change and brightness controllable
 - Lights flash and change color, speed of flash controllable